

## making connections beautifully

Decorative Wiring Accessories • Smart Lighting Control • Wireless Audio


#### 7G2MBSS2BL-B

### Hartland G2 | HARTLAND G2 RANGE | Power Sockets


# Item Image







#### **Dimensions**



Primary Range	Hartland G2
Insert Type	2 gang 13A Double Pole Switched Socket
Insert Colour	Black/Black
EAN13 Barcode	5051164004521
Commodity Code	85363010
Luckins TSI	407517714
Dimensions(Nominal)	Double: Height = 87.4mm Width = 144.4mm Depth = 4.65mm
Weight	265 GR
Switched Poles	Double
Current Rating	13 Amp
Voltage	220/250V AC
Maximum Load	13 Amp
Mains Frequency	50Hz
IP Rating	IP2XD
Contact Gap Minimum	3mm
Terminal Capacity 1	4x2.5mm <sup>2</sup>
Terminal Capacity 2	3x4mm²
Terminal Capacity 3	2x6mm² Multi-Strand
Terminal Capacity 4	lxl0mm²
Earth Terminal Capacity 1	4x2.5mm <sup>2</sup>
Earth Terminal Capacity 2	3x4mm²
Earth Terminal Capacity 3	2x6mm² Multi-Strand
Earth Terminal Capacity 4	lx10mm²
Product Class 1	Must be earthed
Ambient Operating Temperature	-5° to +40°C
Recommended Location	Internal Use Only
Maximum Installation Altitude	2000m
Standard/Approval	BS 1363-2
Additional Notes	Dual Earth: Yes

7G2MBSS2BL-B - Hartland G2 Matt Black 2 gang 13A Double Pole Switched Socket Black/Black



Decorative Wiring Accessories • Smart Lighting Control • Wireless Audio

# 7G2MBSS2BL-B

### Hartland G2 | HARTLAND G2 RANGE | Power Sockets

All products listed conform to current British or European standard and the product information is correct at the time of going to press.

All accessories are manufactured under an accredited BS EN ISO 9001: 2015 Quality Management System.

It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.

Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and match and shadings of of certain are not binding.

Due to manufacturing processes we cannot guarantee an exact colour finishes.

Correct as at 04 May 2022 09:46 AM E&OE

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088

E: info@hamilton-litestat.com www.hamilton-litestat.com Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB Registered in London No. 941624 VAT Registration No. 222 6607 84









7G2MBSS2BL-B - Hartland G2 Matt Black 2 gang 13A Double Pole Switched Socket Black/Black